

One Henkel Way Rocky Hill, CT 06067 Technical Information Help Line 1-800-562-8483 www.equipment.loctite.com

Product Description Sheet Loctite[®] CL10 Quad LED Controller

Item No. 1514634

PRODUCT DESCRIPTION

The Loctite[®] CL10 Quad LED Controller is a UV-LED spot light source that emits UV light at 365 or 405 nm. The Quad Controller includes a footswitch and AC power cord. The required LED head is purchased separately. The maximum number of LED heads that can be installed is four (4) units allowing for multiple cure areas. This system is suitable for manual work stations as well as integration into automated production lines. The CL10 Quad LED Controller can be operated in a continuous light output mode or up to a 10-step, programmed output mode where the light output intensity and time can be programmed for each separate LED head. The cycle can be initiated with the start/stop button on the front panel; a footswitch (included); or via a PLC connection with an external start signal. This LED light source causes no thermal damage or harmful effects to objects being illuminated. Its low power consumption makes it an energy-saving and environmentally friendly light source. No light guides or lamp replacements are required.

CL10 Quad LED Controller

LED Head (each purchased separately)



CONTROLLER PRODUCT FEATURES

- Instant on-off capabilities; no warm-up time required as compared to mercury-arc lamp UV Wand systems.
- Can operate up to four (4) LED heads
- Each LED head can be programmed independently to have a 10-step setting for UV intensity and exposure time.
- Provides five programming modes (constant intensity; pulsed; step; optical; manual).
- Each channel is adjustable and can be controlled separately.
- Temperature feedback to eliminate LED heads overheating.



One Henkel Way Rocky Hill, CT 06067 Technical Information Help Line 1-800-562-8483 www.equipment.loctite.com

Item No. 1514634

TECHNICAL DATA

Quad Controller Item No. 1514634

Modes	C.C	Intensity (0% ~ 100%), Time (0.1 ~ 999.9 seconds)
	Manual	Intensity (0%~100%), Time: Manual control.
	Optical	Especially for optical lens adhesive.
	Step	10 steps, each step can define intensity and time independently.
	PWM	Intensity (0~100%), Time (max 999.9 sec)
Power Supply		100 – 220 VAC; 50/60 Hz. Max. 1.5 amps
Power Consumption		30 Watts
Cooling Method		Natural air cooling
Temperature Range		Operating:+ 5 ~+ 35 Deg. C.; Storage: -15 ~ + 65 Deg. C.
Weight		2 Kg.



365nm LED Head

One Henkel Way Rocky Hill, CT 06067 Technical Information Help Line 1-800-562-8483 www.equipment.loctite.com

Product Description Sheet Loctite[®] CL10 Quad LED Controller

Item No. 1514634

Spot Diameter (mm)6 mmRecommend
Working Distance
(mm)14~16Intensity (mW/cm2)1300Intensity (mW/cm2)1300Wavelength365 nmMaterialAluminum , copper,
optical glassLife cycle20,000~30,000 hours

Spot Diameter (mm)	405nm, LED Head 6 mm
Recommend Working Distance (mm)	8~10
Intensity (mW/cm2)	2000
Wavelength	405 nm
Material	Aluminum , copper, optical glass
Life cycle	20,000~30,000 hours





Irradiation area (mm)

405 LED Head 6mm UV Intensity Profile





One Henkel Way Rocky Hill, CT 06067 Technical Information Help Line 1-800-562-8483 www.equipment.loctite.com

Product Description Sheet Loctite[®] CL10 Quad LED Controller

Item No. 1514634

Dimensions

Quad controller



80.4





NOT FOR PRODUCT SPECIFICATIONS Loctite is a TM of Henkel Corporation, U.S.A. © Copyright 2012. Henkel Corporation. All rights reserved Document: 8903027, Rev D, Date: 02/25/2014



Product Description Sheet Loctite[®] CL10 Quad LED Controller

One Henkel Way Rocky Hill, CT 06067 Technical Information Help Line 1-800-562-8483 www.equipment.loctite.com

Item No. 1514634

Items Available:

	Loctite Item No.					
Quad LED Controller (with 1 Foot switch)	CL10 Quad LED Controller	1514634				
LED Head	CL10 365nm 6mm LED Head, 2.7M Cable	1538499				
(with Lens)	CL10 405nm 6mm LED Head, 2.7M Cable	1746633				
Recommend Spares						
Spare Lens	CL10 365nm 6mm LED Lens	1538496				
	CL10 405nm 6mm LED Lens	1750074				
Spare Foot Switch	Loctite® Foot Switch Assembly	97201				
	Optional Accessories					
	UV V Light Radiometer Dosimeter Assembly	1265282				
	UV A/B Light Radiometer Dosimeter Assembly	1390323				
	Tip Locator for CL10 LED Spot Cure Heads	1403402				